

GPRS SETTINGS FOR VARIOUS MOBILE HANDSETS

ACER
ALCATEL
APPLE I PHONE IPAD
ASUS
BENQ M550C
CHINA MADE MOBILE SET
DOPOD 900 I
FLY or LAVA or MAX
HP IPAQ 6365
HTC
HUAWEI
I-MATE
ION
LG
MICROMAX
MOTOROLA
NOKIA
O2
PALM TREO
SAMSUNG
SIEMENS
SONY ERRICSON
SPICE
VODAFONE or VIDEOCON
VOQ MOBILE

3G DataCard Settings
Configuration of Email Settings
Settings for connecting with laptop

ACER
Internet Settings

Start > Settings > Connections Tab > Connections

Go to MY ISP

1. Add a New modem Connections

Select new

2. Enter a name for the connection: **bslnet**

3. Select a modem: **cellular line (GPRS) then click Next**

4. Access point name: **bslnet then click Next**

5. User name: **blank**

Password: **blank**

Domain: **blank then Finish Save and ok**

To Launch

Start > Settings > Connections Tab > Connections

Go to MY ISP

Manage existing connections

Go to **bslnet > Tap and hold bsnnet > Connect**

Start > Internet explorer

MMS Settings

Start > Settings > Connections tab > Connections

Go to MY ISP

Select New

1. Enter a name for the connection: **bslmms**

2. Select a modem: **cellular line (GPRS) then click Next**

3. Access Point Name: **bslmms then click Next**

4. User name: **blank**

Password: **blank**

Domain: **blank then click Finish Save and ok**

Start > Inbox > Tools > MMS settings

Go to Servers > Tap on Default

4. Server name: **bslmms**

5. Gateway: **10.210.10.11**

6. Server address: **http://bslmmsc.in:8514**

User name: **nil**

Password: **nil**

OK

Go to Preferences >

Connect via: **MY ISP**

Connect to server: **bslmms**

Now you can send **MMS** from your messages in main menu

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no.

ALCATEL

i) OT535 OT 735 OT756

bsnllive Settings

WAP menu > ok > Profile > ok > Profiles list > ok

Create New

1. Profile name: bsnllive
2. Homepage: http://bsnllive.net
3. IP address: 10.220.67.131
4. Security: Normal
5. Bearer choice: GPRS
6. GPRS Parameters
7. Authentication: None or PAP
8. Username: blank
9. Password: blank
10. APN: bsnllive

Validate > ok

11. Profile Parameters > Validate > ok

MMS Settings

1. Menu > ok > Multimedia/MMS > ok

Create MMS profile

2. Profile Name: bsnlmms
3. Service Centre: http:// bsnlmmsc.in:8514
4. IP address: 10.210.10.11
5. Security: Normal
6. Bearer choice: GPRS
- GPRS parameters
7. Authentication: None or PAP
8. User name; blank
9. Password: blank
10. GPRS APN: bsnlmms

Validate > ok

Profile parameters > Validate > ok

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no.

ii) OT 715

bsnllive settings

MENU > Tools > Settings > WAP/GPRS

Access mode > OK.

Select Pref. Access

Go back to MENU > **WAP** > Profiles Click OK. You will get profile parameters:

1. Profile Name: **bsnllive**
2. Homepage: **http://bsnllive.net**
3. IP gateway: **10.220.67.131**
4. Security: **Normal**
5. Bearer choice: **GPRS**
6. Authentication: **None**
7. APN GPRS: **bsnllive**
8. Validate: **OK.**

Select bsnllive at Profiles list and click Launch to access **WAP**.

Go back to MENU and select WAP. It will directly connect to **bsnllive** Wapsite.

MMS Settings

NO MMS facility

iii) OT 835

Bsnl live settings

Menu > WAP > WAP Profiles > Create

1. Title name: **bsnllive**
2. Gateway Primary IP: **10.220.67.131**
3. Gateway Primary Port: **8080**
4. Bearer option: **GPRS**
5. User name: **blank**
6. Password: **blank**
7. GPRS APN: **bsnllive**
8. Homepage: <http://bsnllive.net>

Ok > then Done

Then Set default to activate profile parameters

MMS SETTIGNS

Menu > Message icon > Parameters > MMS Parameter

Create Profile.

1. Title name: **bsnlmms**
2. Gateway Primary IP: **10.210.10.11**
3. Gateway Primary Port: **8080**
4. Bearer: **GPRS**
5. User name: **blank**
6. Password: **blank**
7. GPRS APN: **bsnlmms**
8. Homepage: <http://bsnlmmsc.in:8514>

Ok and Done

Then Set default to activate profile parameters

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no.

Apple i Phone

GPRS Settings to access Internet

Go to MENU > Settings > GENERAL > NETWORK

Go to Cellular data network and type

1 APN: bsnlnet

2 User name and Password: blank

Go to SAFARI to access internet

ii) APPLE I-PHONE 3GS

GPRS Settings to access Internet

Go to MENU > Safari > Data account > GPRS

Edit profile > Select any one profile

1. Account name: bsnlnet
2. APN: bsnlnet
3. User name: nil
4. Password: nil
5. Auth. Type: normal
6. Primary server: 0.0.0.0
7. Secondary server: 0.0.0.0

Save this and Go to Menu > Safari > Internet Service > Settings >

Profiles > Add new

1. Profile name: bsnlnet
2. Homepage: <http://google.co.in>
3. Data account: bsnlnet
4. Conn. Type: http
5. User name: nil
6. Password: nil

Done and Save it.

Select bsnlnet Profile and activate it

Go to MENU > Safari > Home to access homepage

GPRS Settings for Apple iPad

Go to MENU > Settings > Cellular data

Cellular data: ON

Data Roaming: OFF

Data roaming should be made ON when roaming

APN Settings:

1 APN: bsnlnet

2 User name: blank

3 Password: blank

Go to Menu > Safari > Bookmarks > yahoo to access yahoo Homepage

ASUS

GPRS settings for ASUS mobile to access internet.

Start > Settings > Connections tab > Connections

Under My ISP menu > Add a new modem connection

1. Enter a name for the connection: **bsnlnet**
2. Select a modem list: **Cellular Line (GPRS) then click Next**
3. Access point name: **bsnlnet then click Next**
4. User name, Password and Domain: **nil**

Finish and save this.

Starting a data connection

To manually start a data connection

Start > Settings > Connections tab > Connections

1. Manage existing connections.
2. Tap and hold the name of the desired connection, ie **bsnlnet**, then tap **connect**.

To disconnect active data connections

Start > Programs > comm. Manager or

Start > Settings > Connections tab > Conn manager.

1. Tap the data connection button

To open internet explorer on mobile

Tap Start > **internet explorer** > Enter the web site address in the address bar, then tap **GO** button

BENQ M550C

WAP settings to access internet

Menu > Settings > Wap Settings > Up Link Settings

Manual settings then

Bearer select: **GPRS**

ISP Name: **bsnllive**

Home page: **<http://bsnllive.net>**

Gateway Address: **10.220.67.131**

Port: **8080**

Menu > Settings > GPRS settings

APN name: **bsnllive**

User id: **blank**

Password: **blank**

Activate it

To access go to **Services** then **WAP** and **home page**
to access **home page**.

CHINA made mobile set

GPRS Settings for CHINA made mobile set type I

Menu > Services > Data account > GPRS

Select any one profile

Edit

1. Account name : [bsnllive](#) then done then ok
2. APN: [bsnllive](#)
3. User name: [blank](#)
4. password: [blank](#)

then click [WAP](#)

[Settings](#)

[Edit profile](#)

[Sim A](#)

Select any one profile then ok

Edit profile

1. Rename profile: [bsnllive](#)
2. Home page: <http://bsnllive.net>
3. Data account: [bsnllive](#)
4. Connection type: Click select [WAP](#)
5. I P Address : [10.220.67.131](#)
6. Security: [off](#)

Done and save it

To access internet Menu > Services > WAP > Home page

MMS Settings for CHINA made mobile set

Menu > Services > Data account > GPRS

Select any one profile

Edit

1. Account name : [bsnlmms](#) then done then ok
2. APN: [bsnlmms](#)
3. User name: [blank](#)
4. password: [blank save it](#) Then Menu > Messages > MMS > Message settings > Server profile then select [Edit profile](#)

[Sim A](#)

Select any one profile then ok

Edit profile

5. Rename profile: [bsnlmms](#)
6. Home page: <http://bsnlmmsc.in:8514>
7. Data account: [bsnlmms](#)
8. Connection type: Click select **WAP**
9. I P Address : [10.210.10.11](#)
10. Security: [off](#)
11. User name: [blank](#)
12. Password : [blank](#)

Done and save it then activate this profile

To send MMS go to menu>messages>MMS>write message then type any no. then insert any image/audio and send it to this no.

GPRS Settings for CHINA made mobile set type II

Menu > Net service > Browser > Wap settings > Link settings > settings1 >

1. Security connect settings : [enable](#)
2. User name : [blank](#)
3. Password : [blank](#)
4. APN: [bsnllive](#)
5. Gateway : [10.220.67.131](#)
6. port : [8080](#)
7. Rename : [bsnllive](#)

Menu > Net service > Browser > Wap settings > Link settings > SIM1 account settings > [bsnllive](#)

Menu > Net service > Browser > Wap settings > Browser settings > Set homepage > <http://bsnllive.net> then ok

To access internet Menu > Net Service > Browser > Homepage > **Sim1**

You can access home page of [bsnllive](#)

Dopod 900 i

GPRS Settings for Do pod 900

Start > Settings > Connections tab > Connections >
Under My ISP > Add a new modem connection.

1. Enter a name for the connection: bsnlnet
2. Select a Modem: Cellular Line (GPRS) then click
Next
3. APN or Access point name: bsnlnet then click
Next

Username, Password and Domain: blank

Next > Finish > ok > done

To access internet go to internet explorer and type
any URL to access it.

FLY or LAVA or MAX

FLY or LAVA or MAX

For accessing internet

1. Menu > Services > Data account > GPRS > Edit >
2. Account name : bsnllive
3. APN : bsnllive
4. User name : blank
5. Password : blank
6. Authentication type : normal

Done and save it then

Go to Menu > Services > WAP > settings > Edit profile >

1. Rename profile: bsnllive
2. Home page: <http://bsnllive.net>
3. Data account: bsnllive
4. Connection type: WAP
5. IP Address: 10.220.67.131
6. Security: off
7. User name: blank
8. Password: blank

Done and save this

Then activate profile > ok

Menu > Services > Wap > Home page > ok

To access internet.

For MMS settings

Menu > Services > Data account > GPRS > Edit >

1. Account name : bsnlmms
2. APN : bsnlmms
3. User name : blank
4. Password : blank
5. Authentication type : normal

Done and save it then

Go to Menu > Messages> Messages > Message settings > MMS settings
> Server profile >

1. Select profile > edit profile >

Rename profile: bsnlmms

2. Home page: <http://bsnlmmsc.in:8514>

3. Data account: bsnlmms

4. Connection type: WAP

5. IP Address: 10.210.10.11

6. Security: off

7. User name: blank

8. Password: blank

Done and save this

Then activate profile > ok

Menu > Messages > Write Messages > Write MMS > type no. to which
you want send mms > type the subject > insert any slide or image > then
send to send MMS.

HP IPAQ 6365 **General Internet Connection Settings**

Start > Settings > Connection tab > Connections
Go to MY ISP
Select Add a New modem Connections
i) Enter a name for the connection: bsnlnet
ii) Select a modem: cellular line (GPRS)
Press Next
iii) Access point name: bsnlnet
Press Next
User name and Password: nil
And domain should be left blank
Press Next > Finish > Save this

To Launch

Start > Settings > Connections tab > Connections
Go to MY ISP
Manage existing connections > Go to bsnlnet
Tap and hold on bsnlnet > Connect
Start > Internet explorer

MMS Settings

Start > Settings > Connections tab > Connections
Go to MY ISP
New
i) Enter a name for the connection: bsnlmms
ii) Select a modem: cellular line (GPRS)
Next
iii) Access Point Name: bsnlmms
Next
User name and Password: nil
And domain should be left blank
Finish > Save this
Start > Inbox > Tools > MMS settings
Go to Servers
Tap on Default

- i) Server name: **bsnlmms**
 - ii) Gateway: **10.210.10.11**
 - iii) Port: **8080**
 - iv) Server address: **http://bsnlmmsc.in:8514**
 - User name: **nil**
 - Password: **nil**
- Press OK
- iv) Go to Preferences
 - v) Connect via: **MY ISP**
 - vi) Connect to server: **bsnlmms**

Now you can send **MMS** from your messages in main menu

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no.

HTC

GPRS settings for HTC mobile to access internet.

1. Tap **Start > Settings > Connections tab > Connections**
2. My ISP, tap **Add a new modem connection.**
3. Enter a name for the connection: **bsnlnet**
4. In the Select a modem list, select **Cellular Line (GPRS)** Press next
5. Access point name: **bsnlnet**
Press next
6. User name: **nil**
Password: **nil**
And domain should be left blank.
7. Tap **finish.**

Starting a data connection

To manually start a data connection

3. start>Settings>Connections tab>Connections
4. Tap Manage existing connections.
5. Tap and hold the name of the desired connection, i.e. **bsnl**, then tap **connect.**

To disconnect active data connections

2. tap start > Programs>comm. Manager or tap start > settings >connections tab > Conn manager.
3. tap the data connection button

To open internet explorer on mobile

Tap start > **internet explorer.**

To go to a web site

Enter the web site address in the address bar, then tap **GO** button

To access internet from HTC mobile with laptop.

To set up your device as a USB modem

1. **Start > Programs > Internet sharing**
2. In the **PC Connection** list select **USB.**

3. In the **Network Connection** list. Select **the name of the profile** you have created to connect to the internet.
 4. Plug in the **USB** cable between your device and the computer.
 5. Tap **Connect**.
- Once it is connected go to internet explorer and type any URL to access internet.

To **disconnect** the device tap disconnect

ii) HTC S 710

GPRS settings for HTC S 710 mobile to access internet.

1. Tap **Start > Settings > Connections > GPRS >**
2. Select **new> Menu > Add > ok**
3. Description: **bsnlnet**
4. Connects to: **internet**
5. Access point name: **bsnlnet**
6. User name: **nil**
7. Password: **nil**
8. Authentication type: **none**
9. Primary DNS: **blank**
- 10 Secondary DNS: **blank**
11. IP Address: **blank**

Done it

To open internet explorer on mobile

Tap start > **internet explorer**.

To go to a web site

Enter the web site address in the address bar, then tap **GO** button

To disconnect active data connections

4. Tap start > Programs > comm. Manager or tap start > settings> connections tab > Conn manager.
5. tap the data connection button

To access internet from HTC mobile with laptop.

To set up your device as a USB modem

6. **start > programs > internet sharing**
7. In the **PC Connection** list select **USB**.

8. In the **Network Connection** list. Select **the name of the profile** you have created to connect to the internet.
 9. Plug in the **USB** cable bet'n your device and the computer.
 10. Tap **Connect**.
- Once it is connected go to internet explorer and type any URL to access internet.

To **disconnect** the device tap disconnect

GPRS settings for HTC Android mobile to access internet.

Tap Start > Settings > Wireless & Networks > Mobile networks > Access Point Names > New

1. Name: **bsnlnet**
2. APN: **bsnlnet**
3. Proxy: **blank**
4. Port: **blank**
5. User name: **blank**
6. Password: **blank**
7. Server: **blank**
8. MMSC: <http://bsnlmmmsc.in:8514>
9. MMS Proxy: **10.210.10.11**
10. MMS Port; **8080**
11. MCC: **404**
12. MNC: **71**
13. APN Type:

HUAWEI

Huawei GPRS Settings

Menu > Settings > Connectivity > Network access point > New

1. Connect name: [bsnlnet](#)
2. Access point name: [bsnlnet](#)
3. Authentication: [none](#)
4. IP address: [Automatic](#)
5. Primary DNS: [Automatic](#)
6. second DNS: [Automatic](#)

Save this

Menu > Entertainment > Browser > Settings > Internet settings > Browser accounts

Select any one of the profile > Edit

1. Account name: [bsnlnet](#)
2. Homepage: <http://google.co.in>
3. WAP gateway:
 - a. IP address: [000.000.000.000](#)
 - b. Port number: [blank](#)
 - c. User name : [blank](#)
 - d. Password: [blank](#)
4. Connection type: [HTTP](#)
5. Network access point : select [bsnlnet](#)

[Ok](#) it

Options > select [bsnlnet](#) profile > [activate](#) this profile

bsnllive Settings

Menu > Settings > Connectivity > Network access point > New

1. Connect name: [bsnllive](#)
2. Access point name: [bsnllive](#)

3. Authentication: none
4. IP address: Automatic
5. Primary DNS: Automatic
6. second DNS: Automatic

Save this

Menu > Entertainment > Browser > Settings > Internet settings > Browser accounts

Select any one of the profile > Edit

1. Account name: [bsnllive](#)
2. Homepage: <http://bsnllive.net>
3. WAP gateway:
 - a. IP address: [010.220.067.131](#)
 - b. Port number: [8080](#)
 - c. User name : [blank](#)
 - d. Password: [blank](#)
4. Connection type: [HTTP](#)
5. Network access point : select [bsnllive](#)

[Ok](#) it

Options > select [bsnllive](#) profile > [activate](#) this profile

bsnlmms Settings

Menu > Settings > Connectivity > Network access point > New

1. Connect name: [bsnlmms](#)
2. Access point name: [bsnlmms](#)
3. Authentication: none
4. IP address: Automatic
5. Primary DNS: Automatic
6. second DNS: Automatic

Save this

Menu > Messaging > Settings > SMS&MMS > MMS account >

Select any one of the profile > Edit

1. Account name: [bsnlmms](#)

2. MMS centre: <http://bsnlmms.in:8514>
3. WAP gateway:
 - a. IP address: [010.210.010.011](#)
 - b. Port number: [8080](#)
 - c. User name : [blank](#)
 - d. Password: [blank](#)Ok it
4. Connection type: [HTTP](#)
5. Network access point : select [bsnlmms](#)

Options > select [bsnlmms](#) profile > [activate](#) this profile

Mobile TV Settings

Menu > Settings > Connectivity > Network access point > New

1. Connect name: [bsnlstream](#)
2. Access point name: [bsnlstream](#)
3. Authentication: [none](#)
4. IP address: [Automatic](#)
5. Primary DNS: [Automatic](#)
6. second DNS: [Automatic](#)

Save this

Menu > Settings > Connectivity > Streaming settings

1. Default access point: [bsnlstream](#)
2. Streaming gateway: [off](#)
3. QoS: [off](#)

Menu > Entertainment > Browser > Settings > Internet settings > Browser accounts

Select any one of the profile > Edit

1. Account name: [bsnlstream](#)
2. Homepage: [blank](#)
3. WAP gateway:
 - a. IP address: [000.000.000.000](#)

b. Port number: [blank](#)

c. User name : [blank](#)

d. Password: [blank](#)

[Ok](#) it

4. Connection type: [HTTP](#)

5. Network access point : select [bsnlnet](#)

Options > select [bsnlstream](#) profile > [activate](#) this profile to watch Mobile TV

Menu > Entertainment > Browser > Bookmarks > New

1. Title: [mobile tv](#)

2. URL: <http://59.162.166.210/bsnl-3g-wap/request>

[Ok](#) it to save this bookmark

Open this bookmark to browse home page of Mobile TV

You will see the different TV channels icons > Click any Channel icon

You will get one more page where you have to click the link [“New users Click here to subscribe”](#)

Click [“Get Activation Key”](#) link then you will go to [“submy3gtv”](#)

This [SMS](#) is to sent by going to Options > Send

This [SMS](#) will be sent

Exit the [Browser](#) by going to Options

You will get an Activation key through [SMS](#) remember this key.

Now go to

Menu > Entertainment > Browser > Bookmarks > Open [mobile tv](#) bookmark

You will get [home page](#) of all the TV Channels

Click any [channel icon](#) and type the key and submit to [purchase](#) that to watch TV

i-mate

GPRS settings for i-mate mobile to access internet.

1. Start > Settings > Connections tab > Connections
 2. My ISP, tap Add a new modem connection.
 3. Enter a name for the connection: bsnlnet
 4. Select a modem: Cellular Line (GPRS) then tap next.
 5. Enter the Access point name: bsnlnet
 6. User name: nil
Password: nil
- And domain should be left blank.
7. Tap finish.

Starting a data connection

To manually start a data connection

6. tap start>Settings>Connections tab>Connections
7. Tap Manage existing connections.
8. Tap and hold the name of the desired connection, i.e. bsnl, then tap connect.

To disconnect active data connections

6. Tap start > Programs > comm. Manager or tap start > settings > connections tab > Conn manager.
7. tap the data connection button

To open internet explorer on mobile

Tap start>internet explorer.

To go to a web site

Enter the web site address in the address bar, then tap GO button

To access internet from i-mate mobile with laptop.

To set up your device as a USB modem

- 11.start > programs > internet sharing
- 12.In the PC Connection list select USB.
- 13.In the Network Connection list. Select the name of the profile you have created to connect to the internet.

14.Plug in the **USB** cable bet'n your device and the computer.

15.Tap **Connect**.

Once it is connected go to internet explorer and type any URL to access internet.

To **disconnect** the device tap disconnect

ii) I-mate SP3 GPRS settings

Start > Settings > More > Data Connections > Internet connection

Menu > Edit Connections > GPRS Connections > Menu Add

Description: **bsnlnet**

Connects to: **The internet**

Access Point: **bsnlnet**

Username: **nil**

Password: **nil**

Primary DNS: **blank**

Secondary DNS: **blank**

IP Address: **blank**

done

bsnlnet profile is created in GPRS Connections.

Now to access internet go to start, Internet explorer, Menu, Address bar then type any url and say go to connect to that site

Ion

GPRS Settings for Ion make mobile

[Menu](#) > [Services](#) > [Data account](#) > [GPRS](#)

Select any one profile

Edit

- 5. Account name : bsnlnet
- 6. APN: bsnlnet
- 7. User name: blank
- 8. password: blank
- 9. Authentication type : normal
- 10.Primary DNS : blank
- 11.Secondary DNS : blank

[Save this and](#) Then [Menu](#) > [Services](#) > [WAP](#) > [Settings](#)

[Edit profile](#) > [Sim A or Sim B](#)

Select add new then ok

- 7. Account name: bsnlnet
- 8. Home page: <http://www.google.co.in>
- 9. Data account: bsnlnet
- 10.Connection type: select HTTP
- 11.I P Address : blank
- 12.Security: off

Done and save it

To access internet [Menu](#) > [Services](#) > [WAP](#) > [Home page](#)

LG

i) LG - C 3100

Bsnllive settings

Main Menu > Internet

- Select Profiles > Press Options > Add New > Select
- Profile name : bsnllive > OK
- Press Options > Select Settings
- Homepage : <http://bsnllive.net>
- Bearer : GPRS
- Select GPRS settings
- IP Address : 10.220.67.131
- **APN GPRS** : bsnllive > OK
- Select Activate

To Launch > Main Menu > Internet > Home

MMS Settings

Main Menu > Internet

- Select Profiles > Press Options > Add New > Press Select
- Profile name : bsnlmms > OK
- Press Options > Select Settings
- Homepage : <http://bsnlmmsc.in:8514>
- Bearer : GPRS
- Select GPRS settings
- IP Address : 10.210.10.11
- **APN GPRS** : bsnlmms > OK

Main Menu > Messages > Settings > Multimedia message

- Select Network settings

- Go to **Profile** > **Press Options** > **Select Rename**
- Profile name : **bsnlmms**
- Go to **bsnlmms** > **Press options**
- Press **settings**
- Homepage : **http://bsnlmmsc.in:8514**
- Bearer : **GPRS**
- Select **GPRS settings**
- IP Address : **10.210.10.11**
- APN : **bsnlmms**
- Press **Activate**

To **send MMS**

Main Menu > **Messages** > **Write multimedia**

NOTE:

To ensure this setting being activated, go to **Messaging**. Create a **New Multimedia** message by selecting **new message** and select **Multimedia message** and then send to your no. or B party no

ii) LG 8120

WAP Settings

APN

Menu > **Settings** > **Access point** > **Edit**

Connection Title: **bsnllive**

Bearer: **GPRS**

Username: **nil**

Ok and save settings.

BROWSER

Menu > **Browser** > **Settings** > **Profile** > **Edit**

Service name: **bsnllive**

Homepage: http://bsnllive.net
Connection mode: TCP with Proxy
IP address: 10.220.67.131
Proxy server point: 8080
Security: Non Secure
Timeout: 150
Access point: bsnllive

Ok and save settings.

Making sure the ON sign is activated.

MMS

Menu > Messages > Settings > Multimedia message > Multi msg centre > Edit

Title: bsnlmms
MMS URL: http://bsnlmmsc.in:8514
MMS Proxy: 10.210.10.11
Access point: bsnlmms

Ok and save settings.

Making sure the ON sign is activated.

iii) LG B2100

Main Menu > Settings > GPRS settings

When needed

Menu > Internet > Profiles

Options > Rename: bsnllive > ok

Settings

- Homepage : <http://bsnllive.net> > ok
- Bearer > GPRS
- GPRS settings
- IP address : 10.220.67.131 > ok
- User ID: nil
- Password : nil
- DNS : nil
- Connection type:
- Proxy Settings:
- Secure setting > off > activate

To launch

Main Menu > Internet

BSNL MMS Settings

Main Menu > Messages > Settings > Multimedia
Messages > Network Settings

Options > Rename : [bsnlmms](#) > ok

- Select [bsnlmms](#) > Options > Settings
- Homepage : <http://bsnlmmsc.in:8514> > ok
- Bearer : GPRS
- GPRS settings
- IP address : 10.210.10.11 > ok
- APN : [bsnlmms](#) > ok
- Secure setting > off >
- Select activate

To send a **MMS**

Main Menu > Messages > write Multimedia Messages

iv) LG C 1100

WAP Settings

Menu > Internet > Profiles > Options > Setting

- Homepage : **http://bsnllive.net**
- Bearer : **GPRS**
- GPRS settings :

Gateway IP: **10.220.67.131**

APN GPRS: **bsnllive > ok**

Login Name: **nil**

Password: **nil**

- Connection type: **Temporary**
- Proxy settings: **nil**
- DNS : **nil**
- Secure Setting : **nil**
- Display Image: **On**

Rename: **bsnllive**

Activate the settings

To launch **bsnllive > Menu > Internet > Home**

MMS settings

Messages > Settings > Multimedia messages >
Network Settings > Profile > Options >
Settings

1. Homepage : <http://bsnlmmsc.in:8514>
2. Bearer : GPRS

GPRS settings:

3. Gateway IP : 10.210.10.11
4. **APN GPRS** : bsnlmms > ok
5. Login Name : nil
6. Password : nil
7. Connection type: Temporary
8. Secure Setting : *leave default*
9. select Rename : bsnlmms

Activate the settings when finished.

To send a MMS > Menu > Message > Write
Multimedia Message then send to B party
number.

v) **LG C2500**

Menu > Browser > Data account > GPRS > select one of
the GPRS Account > Edit as follows:

1. Account name: bsnllive
2. APN: bsnllive > Save

Browser > Settings > select one of profiles > Edit profile

Name: bsnllive > Save

Home page: <http://bsnllive.net> > Save

Data account > GPRS > **bsnllive**

Connection: **Connection-oriented**

Input: **10.220.67.131** > Save

Activate profile setup completion

Activate

Menu > Browser > WAP > Home > **bsnllive**

MMS Settings

Menu > Messages > Multimedia message > Settings

Edit profile > bsnlmms > Activate profile > setup completion

Homepage: <http://bsnlmmsc.in:8514>

Bearer: **GPRS**

GPRS settings:

Gateway IP: **10.210.10.11**

APN GPRS: **bsnlmms** > ok Send MMS

Menu > Messages > Multimedia message > Write Multimedia message

vi) LG-G 3100

INTERNET SETTINGS

1. Menu → WAP Services → Profiles.

2. Options, then select Rename.

3. Type **bsnllive**

4. Highlight **bsnllive** > **Options** > **Settings**

Homepage: <http://bsnllive.net>
Conn. type: **Permanent**
Conn. security: **Off**
Bearer: **GPRS**

GPRS settings

IP address: 10.220.67.131
APN: bsnllive
User ID: nil
Password: nil

Profiles > highlight **bsnllive**

9. **Options** > **Activate** .

10. To start WAP session return to **WAP Services** > **Home**

11. To finish WAP session press and hold **NO** .

Configuring the Message setting

Menu > Messages > Settings > Multimedia message
> Network settings

Select > New >

- **Rename:** bsnlmms
- **Homepage:** <http://bsnlmmsc.in:8514>
- **Bearer:** **GPRS**
- **GPRS settings:**
 - **IP address:** 10.210.10.11
 - **APN:** bsnlmms
 - **User ID:** nil

- Password: nil
- Connection type: Continuous

vii) LG G7100

BSNL GPRS SETTING FOR GENERAL BROWSING:

Menu > Internet > Profiles > Options > Add new

Name: **bsnllive** > ok

Select this profile > settings

1. Homepage: <http://bsnllive.net>

2. Bearer: GPRS

GPRS settings:

1. IP address: 10.220.67.131

2. APN: bsnllive

3. User ID: nil

4. Password: nil

Display image: **On**

Connection type: Continuous

Secure settings: Off

To launch Go to **Internet** and select **Home**

MMS Settings

Menu > **Messages > Settings > Multimedia Message > Network settings > Select a profile**

Rename: bsnlmms

Homepage: <http://bsnlmmsc.in:8514>

Bearer: GPRS

GPRS settings:

IP address: 10.210.10.11

APN: bsnlmms

User ID: nil

Password: nil

Connection type: Continuous

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no.

viii) GPRS Settings LG G-8000, LG G-5300

1. **Menu » Select Internet » Settings » User Defined 1**
 2. Rename Profile to **bsnllive**
 - a) Homepage: **http://bsnllive.net**
 - b) IP Address: **10.220.67.131**
 - c) Connection mode: **Connection-oriented**
 - d) Security: **Non secure**
 - e) Idle timeout: **180**
 - f) Bearer: **GPRS**
 - g) APN: **bsnllive**
 - h) User ID: **nil**
 - i) Password: **nil**
- Main Menu » Internet » Select Home**

GPRS Settings LG 7020

1. **Menu > Internet > Profiles > Rename >**
2. **bsnllive > activate > settings >**
3. Homepage : **http://bsnllive.net**
4. Conn. : **Continuous**
5. Bearer : **GPRS**
6. **GPRS setting**
7. **IP address : 10.220.67.131**

8. **APN : bsnllive**
9. Go to **Internet** and select **browse**

ix) LG KG300

WAP Settings: Menu > Data account

Menu > Browser > GPRS > Edit to change the data account settings as follows:

1. Account name: **bsnllive**
2. APN: **bsnllive**
3. User Name: **nil**
4. Password: **nil**
5. Authentication: **Normal**

In WAP menu > choose Edit profile in Settings > ok

Choose a profile > ok

Name: **bsnllive**

Home: **http://bsnllive.net**

Data account: GPRS > **bsnllive**

Connection: **Connection-oriented**

Input: **10.220.67.131**

Security: **Off**

Username: **nil**

Password: **nil**

Activate profile > setup completion

Activate

Menu > Browser > WAP > Home

MMS Settings

Menu > Messages > Multimedia message > Settings

Edit profile > bsnlmms > Activate profile

1. Homepage: <http://bsnlmmsc.in:8514>
2. Bearer: GPRS
3. GPRS Settings:

Gateway IP: [10.210.10.11](#)

APN GPRS: bsnlmms

To Send MMS

Menu > Messages > Multimedia message > Write
multimedia message

x) [LG S KU 900 R Settings](#)

**MENU > phone Settings > Connectivity > Access
points > Add new >**

Connection title: [bslnet](#)

Bearer: [GPRS](#)

Authentication: [no auth](#)

User name: [nil](#)

Password: [nil](#)

APN: [bsnlnet](#)

Save this profile

And then go to

Menu > Browser > Settings > Profiles > [Add new](#)

Service name: [bsnlnet](#)

Home page: <http://www.google.co.in>

Connection mode: [TCP without proxy](#)

IP Address: [blank](#)

Proxy server port: [blank](#)

Security: [not secure](#)

Access point: [bsnlnet](#)

To access internet go to menu > browser > home page to connect to the home page

[xii\) LG S 5200](#)

[Menu](#) > [Profiles](#) > [Edit profile](#) > [Rename profile as **bsnllive**](#) > [Edit Profile](#)

Settings:

Homepage: <http://bsnllive.net>

Bearer: **GPRS**

GPRS settings:

1. APN: [bsnllive](#)

2. User ID: [nil](#)

3. Password: [nil](#)

Proxy settings

4. Proxy: [On](#)

IP address: [10.220.67.131](#)

5. Port number: [8080](#)

DNS settings:

6. Primary server: [nil](#)

7. Secondary server: [nil](#)

Micromax

GPRS Settings for Micromax make mobile

Menu > Services > Data account > GPRS

Select any one profile

Edit

12. Account name : [bsnlnet](#)
13. APN: [bsnlnet](#)
14. User name: [blank](#)
15. password: [blank](#)
16. Authentication type : [normal](#)
17. Primary DNS : [blank](#)
18. Secondary DNS : [blank](#)

[Save this and](#) Then Menu > Services > WAP > Settings

[Edit profile > Sim A or Sim B](#)

Select add new then ok

13. Account name: [bsnlnet](#)
14. Home page: <http://www.google.co.in>
15. Data account: [bsnlnet](#)
16. Connection type: Click select [HTTP](#)
17. I P Address : [blank](#)
18. Security: [off](#)

Done and save it

To access internet [Menu > Services > WAP > Home page](#)

To access internet [Menu > Opera Mini Browser >](#)

Type any URL to access internet
OR WAP Settings is as follows

WAP Settings for Micromax make mobile set type I
Menu > Services > Data account > GPRS

Select any one profile

Edit

1. Account name : [bsnllive](#)
2. APN: [bsnllive](#)
3. User name: [blank](#)
4. password: [blank](#)
5. Authentication type : [normal](#)
6. Primary DNS : [blank](#)
7. Secondary DNS : [blank](#)

[Save this and](#) Then Menu > Services > WAP > Settings
[Edit profile > Sim A or Sim B](#)

Select add new then ok

8. Account name: [bsnllive](#)
9. Home page: <http://bsnllive.net>
10. Data account: [bsnllive](#)
11. Connection type: Click select [WAP](#)
12. Use proxy : [yes](#)
13. Proxy Address : [010.220.067.131](#)
14. Proxy port : [8080](#)
15. Security: [off](#)

Done and save it

To access internet [Menu > Opera Mini Browser >](#)
[Type any URL to access internet](#)

MOTOROLA

i) **C650-V600**

General internet Settings (All sites)

1 Press the center button above the mouse key.

Select Web Access.

Go to Web Sessions and select.

Select [New Entry] and press the center button.

Select New.

2 Key in the following:

1. Name: [bsnllive](#)

2. Homepage: <http://bsnllive.net>

3. Service Type1: [WAP](#)

4. Gateway (proxy) IP 1: [10.220.67.131](#)

5. Port 1: [8080](#)

6. Leave Domain1, Service Type2, Gateway IP2, Port

2, Domain 2,

DNS1, DNS2 as unchanged.

7. Timeout: 15 minutes

8. CSD No.1:

9. User Name 1:

10. Password 1:

11. Speed (Bps) 1:14400

12. Line Type 1: ISDN

13. Leave CSD No.2, User Name 2, Password 2,

Speed (Bps)2, Line

Type2 as unchanged.

14. GPRS APN: [bsnllive](#)

15. User Name: [nil](#)

16. Password: [nil](#)

Enter Done.

3 To set GPRS service as the default, Select bsnllive and Press the center button.
Select 'Set default'.

MMS Settings

From the main menu, go to Menu and select Web Access > Web Sessions > [New Entry]

Under Entry Details, select Change and enter the following fields accordingly:

- Name - [bsnlmms](#)
- Homepage - <http://bsnlmmmsc.in:8514>
- Service Type 1 - select [WAP](#)
- Gateway (proxy) IP 1 - [010.210.010.011](#)
- Port 1 - [8080](#)
- Domain 1 - skip
- Service Type 2 - select WAP
- Gateway IP 2 - skip
- Port 2 - 9201
- Domain 2 - skip
- DNS 1 - remain as default (000.000.000.000)
- DNS 2 - remain as default (000.000.000.000)
- Timeout - select 10 minutes
- CSD No. 1 - skip
- User Name 1 - skip
- Password 1 - skip
- Speed (Bps) 1 - select 9600
- Line Type 1 - select ISDN
- CSD No. 2 - skip
- User Name 2 - skip
- Password 2 - skip
- Speed (Bps) 1 - select 9600
- Line Type 1 - select ISDN

- GPRS APN - [bsnlmms](#)
- User Name - [nil](#)
- Password - [nil](#)

Configuring the Message Setting

Press the Menu button.

From the main menu, go to Menu and select Messages > Message Setup > MMS Message Setup > Server Info

- Select mms

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no. or B party no

ii) L6 L7 L9 V3 V3i

Manual configuration for Motorola L6, L7, L9, V3, V3i handsets

Configuration to Access other sites or [bsnllive](#) homepage on GPRS

1 Select **Web Access** from the Main Menu.

Select **Web Sessions**.

Select **[New Entry]**.

2 Key in the following:

Name: [bsnllive](#)

Homepage: <http://bsnllive.net>

Service Type 1: [WAP](#)

Gateway (proxy) IP 1: [10.220.67.131](#)

Port 1: [8080](#)

Leave Domain 1, Service Type 2, Gateway IP 2, Port 2, Domain 2, DNS1, and DNS 2 all empty.

Timeout: 10 minutes

CSD No.1:

User Name1:

Password 1:

Speed (Bps):

Line Type 1: ISDN

Leave CSD No.2, User Name 2, Password 2, Speed (Bps) 2, Line Type 2 all empty

GPRS APN: bsnllive

User Name: nil

Password: nil

Press **done** to save the settings.

3 To launch **BSNL**, go to **Web Sessions** and select **bsnllive** as default.

Configuring the MMS Setting

From the main menu, go to Menu and select Web Access > Web Sessions > [New Entry]

Under Entry Details, select Change and enter the following fields accordingly:

- Name – bsnlmms
- Homepage – <http://bsnlmmsc.in:8514>
- Service Type 1 – select WAP
- Gateway (proxy) IP 1 – 010.210.010.011
- Port 1 – 8080

Leave Domain 1, Service Type 2, Gateway IP 2, Port 2, Domain 2, DNS1, and DNS 2 all empty.

- Timeout – select 10 minutes

Leave CSD No. 1, User Name 1, and Password 1 all empty

- Speed (Bps) 1 – select 9600

- Line Type 1 – select ISDN

Leave CSD No.2, User Name 2, Password 2, Speed (Bps) 2, Line Type 2 all empty

- GPRS APN – [bsnlmms](#)
- User Name – [nil](#)
- Password – [nil](#)

Configuring the Message Setting

Press the Menu button.

From the main menu, go to Menu and select Messages > MMS templates (click on the centre key) > Message Setup > MMS Message Setup > Server Info

- Service Name: [bsnlmms](#)
- Server Name: <http://bsnlmmsc.in:8514>
- Web Session Name: [bsnlmms](#)

iii) MOTO Q 9h

MOTOROLA Q 9h

Start > settings > Connections > GPRS > Click New >

Description: [bslnet](#)

Connects to: [internet](#)

Access Point: [bslnet](#)

User name: [blank](#)

Password: [blank](#)

Authentication type: [None](#)

Primary DNS: [blank](#)

Secondary DNS: [blank](#)

I P Address: [blank](#)

Save this and to access go to Menu > Internet > Favorites > select any > go to access internet

iv) MOTO RCKR E6

Menu > setup > data network > internet profile > new >

Profile name: [bslnet](#)

GPRS settings:

APN: [bslnet](#)

User name: [nil](#)

Password: [nil](#)

Time out: off

Primary gateway IP:

Port:

Secondary gateway IP

Port:

DNS server:

1.

2.

CSD setting:

Dial in number:

Query at logon:

User name:

Password:

Baud rate: auto

Line type:

Time out:

DNS server:

1.

2.

Save

Then menu > browser > left button> setup>profiles> left
button > new > edit profile >

Profile name: [bsnlnet](#)

Home page: <http://google.co.in>

Network link: [bsnlnet](#)

[Save it](#)

v) MOTOROKR Z6

Manual configuration for Motorokr Z6 handsets)

Configuration to Access other sites or bsnllive on GPRS

1 Select **MENU > SETTINGS > CONNECTIONS**

Then **add a connection**

Create new and type following

Profile Name: **bsnllive**

Proxy: **10.220.67.131**

Port: **8080**

Domain:

GPRS APN: **bsnllive**

Next

User Name: **nil**

Password: **nil**

CSD No:

Press **done** to save the settings.

Then Go To **Menu > web access > Brower setup > browser profile > add a new profile > create new**

Profile name: **bsnllive**

Home page: **<http://bsnllive.net>**

Data connection: **bsnllive**

Cookie proxy policy: **let gateway decide**

The save this and

Then Go to **Menu > web access > Brower setup > browser profile > default profile >**

Select **bsnllive** as a **default profile**

Then go to **Menu > web access > Brower** to access internet

1 Select **MENU > SETTINGS > CONNECTIONS**

Then **add a connection**

Create new and type following

Profile Name: **bsnlnet**

Proxy:

Port:

Domain:

GPRS APN: **bsnlnet**

Next

User Name: nil

Password: nil

CSD No:

Press **done** to save the settings.

Then Go to **Menu** > **web access** > **Brower setup** > **browser profile** > **add a new profile** > **create new**

Profile name: **bsnlnet**

Home page: <http://google.co.in>

Data connection: **bsnlnet**

Cookie proxy policy: **let gateway decide**

The save this and

Then Go to **Menu** > **web access** > **Brower setup** > **browser profile** > **default profile** >

Select **bsnlnet** as a **default profile**

Then go to **Menu** > **web access** > **Brower** to access internet

vi) W220

Configuration of Motorola W220 to Access GPRS

1. Press the middle **Menu** key. Then Web access
Next, scroll to **Web Sessions** and Select [**New Entry**].

And Edit Enter the followings:

- Name: **bsnllive**
- Homepage: <http://bsnllive.net>
- Session mode: **permanent**
- Connection security: **off**
- **Data bearer: GPRS**
- GPRS APN : **bsnllive**
- IP Address : **10.220.67.131**

- Authentication type : **Normal**
- User Name: **nil**
- Password: **nil**

- Click 'Done'

To begin accessing GPRS, go to **Menu > Web Sessions**, and select **bsnllive** as default and go to the Browser to go to homepage

GPRS settings for Motorola Android mobile to access internet.

Tap Start > Settings > Wireless control > Mobile networks > Access Point Names >

New

1. Name: **bsnlnet**
2. APN: **bsnlnet**
3. Proxy: **blank**
4. Port: **blank**
5. User name: **blank**
6. Password: **blank**
7. Server: **blank**
8. MMSC: <http://bsnlmmmsc.in:8514>
9. MMS Proxy: **10.210.10.11**
10. MMS Port; **8080**
11. MCC: **404**
12. MNC: **71**
13. APN Type:

Nokia

- i) Nokia 3220 5610 5310 6300 6020 6020i 6030
6070 6080 6230 6230i 6101 6270 6233 7260

General Internet Settings

Nokia 3220_5610_5310_6300_6020_6020i_6030_
6070_6080_6230_6230i_6101_6270_6233_7260

1. Menu > Settings > Configuration settings.
 2. Personal configuration settings > Add new
 3. Services: **Web**
- Key in the following:
4. Account name: **bsnlnet**
 5. Homepage: **<http://google.co.in>**
 6. User name: **nil**
 7. Password: **nil**
 - 7a. use preferred access point: **no**
- Access point settings.
8. Proxy: **DISABLE**
 9. Proxy address: **nil**
 10. Proxy port: **nil**
 11. Data bearer: **GPRS**
- Bearer settings.
12. GPRS Packet data access point: **bsnlnet**
 - 12a Network type: **ipv4**
 13. Authentication: **Normal**
 14. User name: **nil**
 15. Password: **nil**
- Personal Configuration:
16. Options > Activate.

Menu > Settings > Configuration settings > Default Configuration settings > Set Personal configuration settings as default > Activate default in all applications > Yes

Menu > Services > Home to launch the browser

bsnllive Settings

1. Menu > Settings > Configuration settings.
 2. Personal configuration settings > Add new
 3. Services: **Web**
- Key in the following:
4. Account name: **bsnllive**
 5. Homepage: **http://bsnllive.net**
 6. User name: **nil**
 7. Password: **nil**
 - 7a. use preferred access point: **no**

Access point settings.

8. Proxy: **ENABLE**
9. Proxy address: **10.220.67.131**
10. Proxy port: **8080**
11. Data bearer: **GPRS**

Bearer settings.

12. GPRS Packet data access point: **bsnllive**
- 12a Network type: **ipv4**
13. Authentication: **Normal**
14. User name: **nil**
15. Password: **nil**

Personal Configuration:

16. Options > Activate.

Menu > Services > Home to launch the browser

Settings to access WEB Applications:

1. Menu > Settings > Configuration settings.

2. Personal configuration settings > Add new
 3. Services: [Access point](#)
- Key in the following:
4. Account name: [Access point](#)
 5. Homepage:
 6. User name: [nil](#)
 7. Password: [nil](#)
 - 7a. use preferred access point: [no](#)
- Access point settings.
8. Proxy: [DISABLE](#)
 9. Proxy address: [nil](#)
 10. Proxy port: [nil](#)
 11. Data bearer: [GPRS](#)
- Bearer settings.
12. GPRS Packet data access point: [bsnlnet](#)
 - 12a Network type: [ipv4](#)
 13. Authentication: [Normal](#)
 14. User name: [nil](#)
 15. Password: [nil](#)
- Personal Configuration:
16. Options > Activate

It will be activated as personal access point

MMS Settings

1. Menu > Settings > Configuration settings.
2. Personal configuration settings > Add new
3. Services: **Multimedia message**

Key in the following:

4. Account name: **bsnlmms**
5. Homepage: **http://bsnlmmsc.in:8514**
6. User name: **nil**
7. Password: **nil**
- 7a. use preferred access point: **no**

Access point settings.

8. Proxy: **ENABLE**
9. Proxy address: **10.210.10.11**
10. Proxy port: **8080**
11. Data bearer: **GPRS**

Bearer settings.

12. GPRS Packet data access point: **bsnlmms**
- 12a Network type: **ipv4**
13. Authentication: **Normal**
14. User name: **nil**
15. Password: **nil**

Personal Configuration:

16. Options > Activate.

Menu > Messages > Message settings > Multimedia Messages

- Save sent messages: **Yes**
- Allow multimedia reception: **Yes**
- Incoming multimedia messages: **Retrieve**
- Configuration settings
 - > Configuration Settings: **Personal Configuration**
 - Account: **bsnlmms**
- Allow Adverts: **No**

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no.

ii) **Nokia 6210**

BSNLLIVE

Menu > Services > Settings > Active Settings > Settings to be activated > On > Change Active Settings

- Settings name: **bsnllive**
- Homepage: **<http://bsnllive.net>**
- Session Mode: **Permanent**
- Connection Security: **Off**
- Data bearer: **GPRS**
- GPRS Connection: **When Needed**
- GPRS Access Point: **bsnllive**
- IP Address: **10.220.67.131**
- Authentication type: **Normal**
- Login type: **Automatic**
- Username: **nil**
- Password: **nil**

Back to Settings > Active Settings > **bsnllive** > Activate

BSNL MMS

Menu > Services > Settings > Active Settings > Settings to be activated > On > Change Active Settings

- Settings name: **bsnlmms**
- Homepage: **<http://bsnlmmsc.in:8514>**
- Session Mode: **Permanent**
- Connection Security: **Off**
- Data bearer: **GPRS**
- GPRS Connection: **When Needed**
- GPRS Access Point: **bsnlmms**
- IP Address: **10.210.10.11**
- Authentication type: **Normal**
- Login type: **Automatic**
- Username: **nil**
- Password: **nil**

Back to Settings > Active Settings > **bsnlmms** > Activate

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message > New message > Multimedia message and then send to your no.

iii) Nokia 6210 Navigator

bsnllive

Menu > Settings > Phone Settings > Connection > Destinations >

Settings name: **bsnllive**

Data bearer: **packet data**

GPRS Access Point: **bsnllive**

User name: **blank**

Prompt password: **no**

Password: **blank**

Authentication type: **Normal**

Homepage: <http://bsnllive.net>

Use access point: **automatically**

Click options > advanced settings

Network type: **ipv4**

Phone IP address: **automatic**

Name servers: **automatic**

Proxy server address: **10.220.67.131**

Proxy port number: **8080**

Save it

Menu > Services/web > Options > Settings > General > Default
Access Point > **bsnllive**

iv) **Nokia**

**6220 6820 6230 6260 7600 8310 6510 8910 72
10 6610 6100 3530 7250i 6108 3100 3120 3200
3108 3120**

General Internet settings

Menu > Services > Settings > Connection settings

Under Active service setting > Edit active service setting

Settings name: [bsnllive](#)

Homepage: <http://bsnllive.net>

Proxies: [Enable](#)

Primary proxy: [10.220.67.131:8080](#)

Secondary proxy: [nil](#)

Data bearer: [GPRS](#)

Go to bearer settings

Bearer settings:

GPRS access point: [bsnllive](#)

Authentication type: [Normal](#)

Login type: [Automatic](#)

User name: [nil](#)

Password: [nil](#)

Make sure that this setting is activated.

To start using [bsnllive](#) Menu > Services > [Home](#)

MMS Settings

Menu > Services > Settings > Connection settings

Under Active service setting > Edit active service setting

Settings name: [bsnlmms](#)

Homepage: <http://bsnlmmsc.in:8514>

Proxies: [Enable](#)

Primary proxy: 10.210.10.11:8080

Secondary proxy: nil

Data bearer: GPRS

Go to bearer settings

Bearer settings:

GPRS access point: bsnlmms

Authentication type: Normal

Login type: Automatic

User name: nil

Password: nil

To send MMS > Messages > Multimedia messages >
Create message > Insert image/sound clip > Send MMS to
Your no. Or B no. Or Email.

v) Nokia
6600 6670 6680 7610 3230 N70 N72 N73 N76
N82 E70 E71 E90

bsnllive

Menu > Tools > Settings > Connection > Access
points > New Access Point

Connection name: bsnllive

Data bearer: Packet Data

Access point name: bsnllive

User name: nil

Prompt password: No

Password: nil

Authentication **normal**

Homepage: <http://bsnllive.net>

Click Options > Advanced settings

Network type – **ipv4**

Phone IP address: **automatic**

Name servers - : **automatic**

Proxy server address - **10.220.67.131**

Proxy port number: **8080**

BSNLNET

Menu > Tools > Settings > Connection > Access Points > Options
> New Access Point

- Connection Name: **bsnlnet**
- Data Bearer: **Packet Data**
- APN: **bsnlnet**
- Username: **nil**
- Prompt Password: **no**
- Password: **nil**
- Authentication: **Normal**
- Homepage: <http://google.co.in>

Click Options > Advanced settings

Network type – **ipv4**

Phone IP address: **automatic**

Name servers - **automatic**

Proxy server address - **none**

Proxy port number: **0**

Menu > Services/web > Options > Settings > General > Default Access
Point > **bsnlnet**

Email Settings

Menu > Messaging > Option > Settings > Email > Mailboxes > Options > Mailbox.

Mailbox settings:

Mailbox Name: [bsnlmail](#)

Access Point in use: [bsnlnet](#)

My e-mail address: [xxxx@bsnl.co.in](#)

Outgoing mail server: [smtp.bsnl.co.in](#)

Send Message: During next conn.

Username: [<your username>](#)

Password: [<your password>](#)

Incoming mail server: [mail.bsnl.co.in](#)

Mailbox type: **POP3**

Security (ports): **OFF**

APOP secure login: **OFF**

User settings and Automatic retrieval: default

To Send Email: Menu > Messages > Email > Create message > Send to your email address Or B party email address

To retrieve email: Menu > Messaging > bsnlmail > Options > Retrieve email

MMS Settings:

Menu > Tools > Settings > Connection > Access points >

New Access Point

Connection name: [bsnlmms](#)

Data bearer: **Packet Data**

Access point name: [bsnlmms](#)

User name: [nil](#)

Prompt password: **No**

Password: [nil](#)
Authentication: [normal](#)
Homepage: <http://bsnlmmsc.in:8514>
Click Options > Advanced settings
Network type: [ipv4](#)
Phone IP address: [automatic](#)
Name servers: [automatic](#)
Proxy server address: [10.210.10.11](#)
Proxy port: [8080](#)

Menu > Messages > Options > Settings > Multimedia message
Access point in use > [bsnlmms](#)

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no. or B party no

vi) **Nokia 9300**

GPRS Settings

1. On the Desk > [Tools](#) > [Control Panel](#) > [Connections](#) > [Internet setup](#) > [New](#)

Internet settings name: [bsnlnet](#)

Network ID: [Internet](#)

Internet settings type: [GPRS](#)

2. Click next when done with the above and enter the following:

GPRS access point name: [bsnlnet](#)

Password prompts: [No](#)

User name: [nil](#)

Password: [nil](#)

3. Click advanced for more settings and enter the following:

Network type – [IPv4](#)

4. Click the right button to change Proxies settings

Proxy protocol – [HTTP](#)

Use proxy server – NO
Proxy server: nil
Port number: nil
No proxy for – Leave Blank

vii) Nokia 9500 9300

General Internet Settings

Menu > Tools > Control Panel > Connection > Internet setup
New > Popup screen question will appear > No
Internet setup will start > Next
Internet settings name: bsnlnet
Network ID: internet
Internet settings type: GPRS
Next
GPRS Access point name: bsnlnet
Password prompt: No
Username: mobile number: nil
Password: mobile number: nil
Next
Popup screen appears > finish

MMS Settings

Menu > Tools > Control Panel > Connection > Internet setup
New > Popup screen question will appear > No
Internet setup will start > Next
Internet settings name: bsnlmms
Network ID: internet
Internet settings type: GPRS
Next
GPRS Access point name: bsnlmms
Password prompt: No
Username: nil
Password: nil
Next
Popup screen appears > Advance
Go with the upper tabs to > Proxies

Proxy protocol: wap
Use proxy server: Yes
Proxy server: 10.210.10.11
Port number: 8080
Done and Finish
Now go to step 2

Step Number 2:

Menu > Personal > Messaging icon
Menu > Tools > Account settings > Multimedia message service
Edit > at the second tab (Send)
Internet access: bsnlmms
Homepage: http://bsnlmmsc.in:8514
Receive report: No
Sending time: Immediately
Validity period: Maximum
At the second tab (Receive)
Multimedia messages reception: Always enabled
Receive Multimedia messages: On
Receive Advertisements: Yes
Receive anonymous messages: Yes
At the third tab (General)
Compress images: No
(Done)

viii) Nokia
N79 N85 N93 N96 5800ExpressMusic 5700

BSNLNET

Menu > Tools > Settings > Connectivity > Destinations >
Access points > Add new access point
Automatically check for available access points: No >
select access point: packet data

Packet data access point name: [bsnlnet](#)
Destination: [internet](#)
Packet data access point will be added then select this
access point and edit
Connection name: [BSNL GPRS](#)
Data bearer: **Packet Data**
Access point name: [bsnlnet](#)
User name: [blank](#)
Prompt password: [No](#)
Password: [blank](#)
Authentication: [normal](#)
Homepage: <http://google.co.in>
Use access point: [automatically](#)
Options > advanced settings
Network type – [ipv4](#)
Phone IP address: [automatic](#)
DNS addresses - : [automatic](#)
Proxy server address - [none](#)
Proxy port number: [0](#)

To access internet make this profile as Default by going to
Menu > Services/web > Options > Settings > General >
Access Point > User defined > [bsnlnet](#)

ix) **Nokia N900**
General Internet Settings

Menu > Settings > Connectivity > Internet connections >
Connections > New
Set up wizard will start

1. Connection name : [bsnlnet](#)
 2. Connection type : [Packet data](#)
- Next
- Access point name: [bsnlnet](#)
- User name: [blank](#)
- Password: [blank](#)
- Uncheck Prompt password at every login
- Nothing is required in advanced settings.
- Finish

To access internet go to web and type any URL and go

x) **Nokia Ngage-Qd**

Nokia Ngage QD

1. Menu > Settings > Connections > Access points you will be prompted with a message: “No access points defined. Define now?” Select Yes.
2. Key in the following:
Connection name: [bsnllive](#)
Data bearer: [GPRS](#)
Access point name: [bsnllive](#)
User name: [nil](#)
Prompt password: [No](#)
Password: [nil](#)
Authentication: [Normal](#)
Homepage: <http://bsnllive.net>
Gateway IP address: [0.0.0.0](#)
Connection security: [off](#)
Session mode: permanent
Options then advanced settings

Device IP address: [automatic](#)
Primary name servers: [0.0.0.0](#)
Secondary name server: [0.0.0.0](#)
Proxy server address: [10.220.67.131](#)
Proxy port number: [8080](#)

3. to launch GPRS service,
Go to Menu > Web > bsnllive as the default access point in
Setting.

[MMS Settings](#)

1. Menu > Settings > Connections > Access points you will
be prompted with a message: “No access points defined.
Define now?” Select Yes.

2. Key in the following:

Connection name: [bsnlmms](#)

Data bearer: [GPRS](#)

Access point name: [bsnlmms](#)

User name: [nil](#)

Prompt password: [No](#)

Password: [nil](#)

Authentication: [Normal](#)

Homepage: <http://bsnlmmsc.in:8514>

Gateway IP address: [0.0.0.0](#)

Connection security: [off](#)

Session mode: permanent

Options then advanced settings

Device IP address: [automatic](#)

Primary name servers: [0.0.0.0](#)

Secondary name server: [0.0.0.0](#)

Proxy server address: [10.210.10.11](#)

Proxy port number: [8080](#)

MMS Settings

Select **MENU > SETTINGS > CONNECTIONS**

Then add a connection

Create new and type following

Profile Name: **bsnlmms**

Proxy: **10.210.10.11**

Port: **8080**

Domain:

GPRS APN: **bsnlmms**

THEN CLICK **Next**

User Name: **nil**

Password: **nil**

CSD No:

Press **done** to save the settings.

From the main menu, go to **Menu** and select **Messages > options > settings > Multimedia Messages > Service profiles > create**

Profile name: **bsnlmms**

Service centre: **http://bsnlmmsc.in:8514**

Internet connection: **bsnlmms**

Press **done** to **save** the settings.

Then click **active service profile** and select **bsnlmms** profile here as a default profile

xi) Nokia E72 E75 C5

BSNLNET

Menu > Control panel > Settings > Connection

>Destinations > Add new access point

Automatically check for available access points: No >

select access point: packet data

Packet data access point name: bsnlnet

Destination: internet

Packet data access point will be added then select this access point and edit

Connection name: **BSNL GPRS**

Data bearer: **Packet Data**

Access point name: **bsnlnet**

User name: **blank**

Prompt password: **No**

Password: **blank**

Authentication: **normal**

Homepage: <http://google.co.in>

Use access point: **automatically**

Options > advanced settings

Network type – **ipv4**

Phone IP address: **automatic**

DNS addresses - : **automatic**

Proxy server address - **none**

Proxy port number: **0**

To access internet make this profile as Default by going to
Menu > Services/web > Options > Settings > General >
Access Point > User defined > **bsnlnet**

O2

O2XDAII

General Internet Settings

Start > Settings > Connections tab > Connections

Click on the "Add a new modem connection"

Enter the following things

i) Enter a name for the connection: **bslnlnet**

ii) Select a Modem: **Cellular Line GPRS**

Press Next

iii) Access point Name: **bslnlnet**

Press Next

iv) User Name: **nil**

v) Password: **nil**

vi) Domain: **nil**

Verify that in the advanced tab

In TCP/IP

1) Use server assigned IP address

In Servers

2) Use server assigned address

MMS Settings

STEP 1:

Start > Settings > Connections tab > Connections

Click on the "Add a new modem connection"

Enter the following things

i) Enter a name for the connection: **bsnlmms**

ii) Select a Modem: **Cellular Line GPRS**

Press Next

iii) Access point Name: **bsnlmms**

Press Next

iv) User Name: **nil**

v) Password: **nil**

vi) Domain: **nil**

Verify that in the advanced tab

In TCP/IP

1) Use server assigned IP address

In Servers

2) 1) Use server assigned address

STEP 2:

On the main Screen click on the link “NO New MMS message “
Tools > Options > Preferences

Fill in the following options

i) Connect Via: My ISP

ii) Connect to Server: “at present leave it as Sample Server”

And rest all leave them default.

Now go to Servers option

Create a new one with the following info

1) Server name : **bsnlmms**

2) Gateway : **10.210.10.11**

3) Server Address: **<http://bsnlmmsc.in:8514>**

4) Then **ok**

NOTE: To ensure this setting being activated, go to Messaging
> Multimedia message > New MMS > and then send to your no.

Palm treo

GPRS setting in palm Treo 650

All you need to do is enable the APN (Access Point Name), which you can do as follows...

Web: Connection Settings (Web)

1. Go to > Preferences > Communication > network

Then click modify button for editing information.

2. Name of service: bsnlnet

3. Choose connection as GPRS

4. Username: nil

4a password: nil

5. Name APN as: bsnlnet

Then click details tab Under Advanced settings, make sure ip address is set to automatic and Query DNS is enabled.

Then done it

Samsung

i) GT B7320

GPRS settings for Samsung B 7320 mobile to access internet.

Tap **Start** > **Settings** > **Connections** > **GPRS** > **New**

1. Description : **bsnlnet**
2. Connects to : **The internet**
3. Access point : **bsnlnet**
4. User name : **blank**
5. Password : **blank**
6. Authentication type : **none**
7. Primary DNS : **blank**
8. Secondary DNS : **blank**
9. IP address : **blank**

Go to Internet explorer > Menu > Tools > Options > Connections > Select Network: **The internet**

Done it

To open internet explorer on mobile

Tap start > **internet explorer**.

To go to a web site

Enter the web site address in the address bar, then tap **GO** button

ii) GT S5233A(2G) S5603(3G)

GPRS settings for Samsung B 7320 mobile to access internet.

Tap **Start** > **Settings** > **Connections** > **GPRS** > **New**

10. Description : **bsnlnet**
11. Connects to : **The internet**
12. Access point : **bsnlnet**
13. User name : **blank**
14. Password : **blank**
15. Authentication type : **none**
16. Primary DNS : **blank**
17. Secondary DNS : **blank**
18. IP address : **blank**

Go to Internet explorer > Menu > Tools > Options > Connections > Select Network: **The internet**
Done it

To open internet explorer on mobile

Tap start > **internet explorer**.

To go to a web site

Enter the web site address in the address bar, then tap **GO** button

iii) **GT S 3653 Corby and S8500**

GPRS settings for Samsung GT-S3653_Corby AND S8500 mobile to access internet.

1. **Menu > Settings > Application Settings > Internet > Internet > Create >**
2. Set name: **bsnlnet**
3. Access name: **bsnlnet**
4. Auth type: **Normal**
5. User id: **blank**
6. Password: **blank**
7. Protocol: **http**
8. Home URL: **http://google.co.in**
9. Proxy address: **blank**

10. Secure connection: **off**
 11. Linger time (Sec.): **default**
 12. Advanced settings:
 - Static IP: **blank**
 - Static DNS: **blank**
 - Traffic class: **Subscribed**
- Save it

Go to internet explorer and click Home to access home page
GPRS settings for Samsung GT-S3653_Corby mobile to access wap

1. Tap **Menu > Settings > Application Settings > Internet > Internet profiles > Create >**
 2. Set name: **bsnllive**
 3. Access name: **bsnllive**
 4. Auth type: **Normal**
 5. User id: **nil**
 6. Password: **nil**
 7. Protocol: **http**
 8. Home URL: **http://bsnllive.net**
 9. Proxy address: **10.220.67.131**
 10. Secure Connection: **off**
 11. Linger time (Sec.): **default**
 12. Advanced Settings:
 - Static IP: **blank**
 - Static DNS: **blank**
 - Traffic class: **Subscribed**
- Save it

Go to internet explorer and click Home to access home page

iv) i710 i900

GPRS settings for Samsung i710_i900 mobile to access internet.

1. Tap **Start > Settings > Connections tab > Connections**

2. My ISP, tap **Add a new modem connection**.
 3. Enter a name for the connection: **bsnlnet**
 4. In the Select a modem list, select **Cellular Line (GPRS)**, and then tap Next
 5. Enter the Access point name as: **bsnlnet**
 6. User name: **nil**
Password: **nil**
- And domain should be left blank.
7. Tap **finish**.

Starting a data connection

To manually start a data connection

9. tap start > Settings > Connections tab > Connections
10. Tap Manage existing connections.
11. Tap and hold the name of the desired connection, ie **bsnlnet**, then tap **connect**.

To disconnect active data connections

8. Tap start > Programs > comm. Manager or tap start > settings > connections tab > conn manager.

9. tap the data connection button

To open internet explorer on mobile

Tap start > **internet explorer**.

To go to a web site

Enter the web site address in the address bar, then tap **GO** button

v) **SGH X660 D780**

SAMSUNG SGH_X660_D780

Menu > **Browser** > **WAP profile** > **Create?** > **Yes**

- Profile name : [bsnllive](#)
- Homepage URL : <http://bsnllive.net>
- Proxy : yes
- IP address : [10.220.67.131](#)
- Port : [8080](#)
- Bearer : [GPRS](#)
- Go to [Advanced settings](#)
- APN : [bsnllive](#)

[Save](#) this

Main Menu > [Browser](#) > [WAP profile](#)

- Go to [bsnllive](#) > [Options](#) > Activate

To launch Menu > [Browser](#) > [Home](#)

MMS Settings

Menu > Messages > Settings > Multimedia message
> MMS profiles > Profile setting > Profile 1

- Profile name : [bsnlmms](#)
- Homepage URL : <http://bsnlmmsc.in:8514>
- Proxy : Yes
- IP address : [10.210.10.11](#)
- Port : [8080](#)
- Bearer : [GPRS](#)
- Go to [Advanced settings](#)
- APN : [bsnlmms](#)

[Save](#) it

Main Menu > [Messages](#) > [Settings](#) > [Multimedia](#)

message > MMS profiles > Current profile

- Select [bsnlmms](#)

To [send MMS](#)

Main Menu > [Messages](#) > [Create new message](#) >
[Select Multimedia message](#)

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no. or B party no.

vi) **Samsung**

SGH X700 E800C E330C E100A E700A
S200 S300 S500 X100A X600A V200C
C100 X400 X430

bsnlnet SETTING FOR INTERNET BROWSING:

Main Menu > Fun Box or [Browser](#) > [Profile settings](#) > [Profile 1](#) > [Edit](#)

1. Profile name: [bsnllive](#)
 2. Home URL: <http://bsnllive.net>
 3. Bearer: [GPRS only](#)
 4. Proxy: [Enable](#)
- [GPRS settings](#)
5. Proxy IP : [10.220.67.131](#)
 6. Proxy port : [8080](#)
 7. APN: [bsnllive](#)

Save this

Main Menu > [Browser](#) > [Current profile](#) > [bsnllive](#) > make it default

To launch go to [Menu](#) > [Browser](#) > [Home](#)

MMS Settings

[Menu](#) > [Messages](#) > [Settings](#) > [Multimedia message](#) > [MMS profiles](#) > [Profile settings](#) > [Profile 1](#) > [Edit](#)

1. Profile name: [bsnlmms](#)
 2. Server URL: <http://bsnlmmmsc.in:8514>
 3. Proxy: [Enable](#)
- GPRS settings
4. Proxy IP: [10.210.10.11](#)
 5. Proxy port: [8080](#)
- viii APN: [bsnlmms](#)

Save this

Main Menu > Messages > Settings > Multimedia message > MMS profiles > Current profile > [bsnlmms](#) > Press Select

To send MMS

Main Menu > Messages > Create new message > Multimedia message

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no. or B party no.

vii) Samsung Android i7500_i9000

Tap Start > Settings > Wireless control > Mobile networks > Access Point Names >

New

1. Name: [bsnlnet](#)
2. APN: [bsnlnet](#)
3. Proxy: [blank](#)
4. Port: [blank](#)
5. User name: [blank](#)
6. Password: [blank](#)
7. Server: [blank](#)
8. MMSC: <http://bsnlmmmsc.in:8514>
9. MMS Proxy: [10.210.10.11](#)
10. MMS Port; [8080](#)
11. MCC: [404](#)
12. MNC: [71](#)
13. APN Type:

Siemens

Configuration of Siemens S45/ ME45

Menu > Surf & fun > Internet > Profiles > Profile 1 > Edit.

1. **Profile name: bsnllive**

WAP Parameters

2. IP address: **10.220.67.131**

3. Port: **8080**

4. Homepage: **http://bsnllive.net**

5. Linger time: **120**

GPRS settings

6. APN: **bsnllive**

7. Login name: **nil**

8. Password: **nil**

Under **Menu > Setup > Connectivity >** and check **GPRS**

You should see the word **GPRS** on top of your screen.

To begin accessing **bsnllive**

Go to **Menu > Surf & fun > Internet > Homepage**

Sony erriccson

i) Experia

GPRS settings for Experia mobile to access internet.

1. Tap **Start > Settings > Connections tab > Connections**
2. My ISP, tap **Add a new modem connection.**
3. Enter a name for the connection: **bsnlnet**
4. In the Select a modem list: **Cellular Line GPRS**

Next

5. Access point name as: **bsnlnet**

Next

6. User name: **nil**

 Password: **nil**

 Domain should be left blank.

7. Tap **finish.**

Starting a data connection

To manually start a data connection

12. tap start > Settings > Connections tab > Connections
13. Tap Manage existing connections.
14. Tap and hold the name of the desired connection, ie **bsnlnet**, then tap **connect.**

To disconnect active data connections

10. Tap start > Programs > comm. Manager or tap start > settings > connections tab > Conn manager.
11. tap the data connection button

To open internet explorer on mobile

Tap start > **internet explorer**.

To go to a web site Enter the web site address in the address bar, then tap **GO** button

ii) G502 W910i U100i C510 J105i AINO U10

General Internet Connection Settings

• Main Menu > Settings > Connectivity > Internet settings > Connect using > Options > Create new > ps data >

• Name: **bsnlnet**

• APN : **bsnlnet**

Save it a data account will be created.

Menu > Settings > Connectivity > Internet settings > Connect using > **bsnlnet**

Save this

To access internet go to Menu > Internet > Options > Go to > Bookmarks or Enter address then say go

iii) K750i J230i W810i K310i K700i K500i W200i K810i

BSNLLIVE SETTING

Menu > Settings > Connectivity > Data comm. > Data accounts > Add New account > GPRS data

1. Name: **bsnllive**
2. APN: **bsnllive**
3. User name: **nil**
4. Password: **nil**

Save this

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > Add New profile >

5. Name: **bsnllive**
6. Connect using: **bsnllive**

Save this

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > bsnllive > More > Settings

5. Connect using: **bsnllive**
6. Internet mode: **HTTP**
7. Use proxy: **yes**
8. Proxy address: **010.220.067.131**
9. Port number: **8080**

Save this

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > bsnllive > More > Advanced

10. Change homepage:
Name: **bsnllive**
Address: <http://bsnllive.net>

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > Select profile > **bsnllive**

To launch home page of bsnllive

Go to Menu > Internet services > More > bsnllive

MMS SETTINGS

Menu > Settings > Connectivity > Data comm. > Data accounts > New account > Add > GPRS data

7. Name: **bsnlmms**
8. APN: **bsnlmms**

Save this

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > New profile > Add

9. Name: **bsnlmms**
10. Connect using: **bsnlmms**

Save this

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > bsnllive > More > Settings

5. Connect using: **bsnlmms**
6. Internet mode: **HTTP**
7. Use proxy: **yes**
8. Proxy address: **010.210.010.011**
9. Port number: **8080**

Save this

Go to Menu > Settings > Connectivity > Internet settings > Internet profiles > bsnllive > More > Advanced

10. Change homepage:
Name: **bsnlmms**
Address: <http://bsnlmmsc.in:8514>

Main Menu > Messaging > Picture message > Options

Message server: <http://bsnlmmsc.in:8514>

Internet profile: **bsnlmms** > ok

To send MMS

Menu > Messaging > Picture message > Write new > Insert Picture > Send to your no. or B No.

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no. or B Party no.

iv) P800-P900

General Internet Settings

Menu > Control panel > Connections > Internet accounts > Accounts > New Internet account:

- 1 Account name: **bsnlnet**
- 2 Connection type: **GPRS.**
3. Address: **bsnlnet**

Log in tab:

4. Username and password should be: **nil**

Advanced tab: Server:

5. Get IP address and Get DNS address:
automatically.

Proxy tab;

6. Uncheck Use proxy server: **nil**

Other tab:

7. Check Enable PPP extensions and
Authentication: **None**

Done and save it

MMS Settings

Menu > Control panel > Connections > Internet accounts >
Accounts > New Internet account:

1 Account name: **bsnlmms**

2 Connection type: **GPRS**

3. Address: **bsnlmms**

Advanced tab: Server:

4. Get IP address and Get DNS address:
automatically.

Log in tab:

5. Username and password should be: **NIL**

Proxy tab;

6. Uncheck Use proxy server: **NIL**

Done and save it

7. Check Enable PPP extensions and
Authentication: **None**

At Internet accounts > other:

Dial-up timeout: **5 minutes (optional)**

GPRS timeout: **5 minutes (optional)**

Preferred mode: **GPRS only**

Done it

At Control panel > Connections > WAP accounts > Basic
> New

- 1 Account name: **bsnlmms**
- 2 Internet account: **bsnlmms**
- 3 Check Use Proxy: **Yes**
- 4 Addresses: **10.210.10.11**
- 5 Ports: **8080**
- 6 Username: **nil** and Password: **nil**

Click done and save it

At WAP accounts > Preferred > WAP account > Preferred
> bsnlmms > done and save it

Go back to Application Menu (step 1) and select Internet

Click at Open page > APN GPRS: **bsnlmms**

Select Messaging accounts: **bsnlmms**

- 1 Service centre address: <http://bsnlmmsc.in:8514>
- 2 WAP account: **bsnlmms**
- 3 Automatic: **On**
- 4 Download size: **No restrictions**

Other parameters in Advanced are optional > done

To send MMS Menu > Messages > MMS Message > New
> Add image and send to your no.

v) **P910i P1i W960i P990i**

GPRS settings for P910i_P1i_W960i **P990i**

1 **Menu > Tools > Control panel > Connections Tab >**

Internet Accounts > New > Type of account: data

Key in the following:

1. Account name: **bsnlnet**

2. Address: **bsnlnet**

Uncheck Select User name and password required: no

3. User name: **nil**

4. Password: **nil**

TCP/IP Tab:

5. Get IP address **automatically** and Get DNS address **automatically**

Proxy Tab:

6. **Uncheck** the option 'Use proxy server'

Login tab:

7. **Enable PPP extensions.**

8. Authentication: **None**

Done and save it

vi) **Sony Ericsson T230 T610 T630 Z200 Z600**

General Internet Settings

Menu > Connectivity > Data comm.

Data accounts > New account > GPRS data

1. Name: **bsnllive > ok**

2. APN: **bsnllive > ok**

Save? > **Yes**

• Menu > Web services > WAP Profile > New

3. Name: **bsnllive > ok**

4. Connect using: > **bsnllive > ok**

5. IP address: 10.220.67.131 > ok

6. Homepage: http://bsnllive.net

Save? > Yes

- To Launch Menu > WAP Services > Home

MMS Setting For Sony Ericsson T610, T630, Z600

Step 1 : Configuring the Service settings

Connectivity > Data Comm. > Data accounts > New account > **GPRS data**

1. Name: **bsnlmms**

2. APN: **bsnlmms**

3. User name: **nil**

4. Password: **nil**

Step 2: Configuring the WAP services settings

Connectivity > WAP options > WAP profiles > New profile

1. Name: **bsnlmms**

2. Connect using: **bsnlmms**

3. IP address: **10.210.10.11**

Advanced > Change homepage

4. Name: **bsnlmms**

5. IP Address: **http://bsnlmmmsc.in:8514**

6. Security: **Off**

7. Show pictures: **On**

Step 3: Configuring the Message settings

Messaging > **Picture**> Options

8. Validity period: **Maximum**

9. Read Report; **Off**

10. Delivery Report: **Off**

11. Content alert: **On**

12. Message server: **http://bsnlmmmsc.in:8514**

13. WAP Profile: **bsnlmms**

Messaging > **WAP push** > **Allow push** > **Always**

To send MMS

Menu > messages > MMS > Create new

NOTE: To ensure this setting being activated, go to Messaging. Create a New Multimedia message by selecting new message and select Multimedia message and then send to your no. or B party no

vii) Sony ericsson Xperia X10i Android

Tap Start > Settings > Wireless control > Mobile networks
> Access Point Names >

New

1. Name: [bsnlnet](#)
2. APN: [bsnlnet](#)
3. Proxy: [blank](#)
4. Port: [blank](#)
5. User name: [blank](#)
6. Password: [blank](#)
7. Server: [blank](#)
8. MMSC: <http://bsnlmmmsc.in:8514>
9. MMS Proxy: [10.210.10.11](#)
10. MMS Port; [8080](#)
11. MCC: [404](#)
12. MNC: [71](#)
13. APN Type:

viii) Sony ericsson Vivaz pro U8i

Menu > Tools > Settings > Connectivity > Destinations >
Access points > Add new access point

Automatically check for available access points: [No](#) >
select access point: [packet data](#)

Packet data access point name: [bsnlnet](#)

Destination: [internet](#)

Packet data access point will be added then select this access point and edit

Connection name: **BSNL GPRS**

Data bearer: **Packet Data**

Access point name: **bsnlnet**

User name: **blank**

Prompt password: **No**

Password: **blank**

Authentication: **normal**

Homepage: **<http://google.co.in>**

Use access point: **automatically**

Options > advanced settings

Network type: **ipv4**

Phone IP address: **automatic**

DNS addresses: **automatic**

Proxy server address: **none**

Proxy port number: **0**

To access internet make this profile as Default by going to
Menu > Services/web > Options > Settings > General >
Access Point > User defined > **bsnlnet**

Spice

SPICE_555_D88_S9_M5252_S590

Go to Menu > Settings > Network Selection > GPRS connection

Go to Menu > Services > Data accounts > GPRS

1. Account name : [bsnllive](#)
 2. APN: [bsnllive](#)
 3. User name : [blank](#)
 4. Password : [blank](#)
 5. Authentication type : [Normal](#)
- Save this profile and

Then Menu > Services > WAP > Settings > Edit Settings > bsnllive

Rename profile: [bsnllive](#)
Home page: <http://bsnllive.net>
Data account: [bsnllive](#)
Connectivity: [connection oriented](#)
I P Address: [10.220.67.131](#)
Security: [off](#)
User name: [nil](#)
Password: [nil](#)

Then done

SPICE D88 hand set

Go to Menu > Settings > Connect Setting > GPRS

1. Account name: [bsnllive](#)
2. APN: [bsnllive](#)
3. User name : [nil](#)
4. Password : [nil](#)
5. Authentication type : [Normal](#)
6. 1st Gateway : [10.220.67.131](#)
7. 2nd gateway : [0.0.0.0](#)
8. port : [8080](#)

Then go to Menu > Services > Data accounts > GPRS

Then Menu > Services > WAP > Settings > Edit profile > bsnllive

Account: [bsnllive](#)

Home page: <http://bsnllive.net>

Connect type: [continue \(http\)](#)

Auto offline: [none](#)

Then done and save the profile

Go to the browser to access internet

WAP Settings for SPICE S-9 hand set

Go to Menu > Settings > Network Selection > GPRS connection > when needed

Then go to Menu > Services > Data accounts > GPRS

1. Account name : [bsnllive](#)
2. APN: [bsnllive](#)
3. User name : [nil](#)
4. Password : [nil](#)
5. Authentication type : [Normal](#)

Save this profile and

Then Menu > Services > WAP > Settings > Edit Settings > bsnllive

Modify name: [bsnllive](#)

Home page settings: <http://bsnllive.net>

Gateway settings: [10.220.67.131](#)

Port settings: [8080](#)

Net account: [bsnllive](#)

Then done and save this profile

To access internet

Menu > Services > WAP > Home

—

Vodafone or VIDEOCON

Settings for VODAFONE or VIDEOCON mobile

Menu> settings > browser > profiles > ok > add

1. provider title : bsnllive
2. Home page: <http://bsnllive.net>
3. protocol: wap
4. preferred Conn. : gprs
5. proxy: use > yes
6. login: nil
7. password: nil
8. proxy address: 10.220.67.131
9. port number : secure > ok > 8080
10. GSM parameters
 - a. login: nil
 - b. password: nil
 - c. dial-up no:
 - d. mode: digital
11. GPRS parameters:
 - A. login: nil
 - B. password: nil
 - C. APN: bsnllive

Save and activate this profile

Vog Mobile

Start > more > Settings > more > Data connections > Menu > Edit connections > More > GPRS connections > click Menu then Add

Type the following information

1. Description: [bslnet](#)
 2. Connects to: [internet](#)
 3. Access point: [bslnet](#)
 4. User name: [nil](#)
 5. Password: [nil](#)
 6. Authentication type: [none](#)
 7. Primary DNS:
 8. Secondary DNS:
 9. IP Address:
- Done

For accessing internet > Go to start > [internet explorer](#) > then [favorites](#) > [Google](#) > Go

3G Data Card Settings for Huawei Teracom Micromax

3G Data Card Settings for Huawei Data Card USB type

Open Mobile partner application

Go to Tools > Options > Profile Management > Click Edit button

In APN field type **bsnlnet** in place of **gprssouth.cellone.in**

Save this > Now Open Mobile partner application and click **connect**

If you want to create new profile

Open Mobile partner application

Go to Tools > Options > Profile Management > Click New

1. Profile name : **bsnlnet**
2. Check **static**
3. APN : **bsnlnet**
4. Dial no. access no. : ***99#**
5. User name and password : **blank**

Save this profile as a default and then **connect**.

3G Data Card Settings for Teracom Data Card USB Type

Open BSNL 3G application

Go to Settings > Connections > Profile

Two Profiles will be displayed

1. BSNL 3G
2. BSNL 3G SOUTH

Select BSNL 3G Profiles and click Set default button then apply

Now go to internet and connect

Micromax Data Card Settings

Open USB Modem application > Click Settings > Select Connection Profile > Add

Under New Connection Profile Check New Profile > Click Next and type as below Under Profile Menu

Profile Name:	bsnlnet
Dial No. :	*99#
User Name:	blank
Password:	blank
APN:	bsnlnet
Auth Type: Select	NONE

Click Finish and set this Profile as default Profile then connect to access internet

Configuration of Email Settings

Setup BSNLmail For Mobile

How to manually setup your BSNL mail on your mobile phone. Pl. Follow the following steps.

1. Open Messaging > Options button >Settings > E-mail then
2. Go to Mail box > Options > New mailbox then
- 3. In Mailbox settings**
4. Mailbox : [bsnlmail](#)
5. Access point in use : select [bsnlnet](#) or [bsnllive](#)
6. My e-mail address : xxx@bsnl.co.in
7. Outgoing mail server : smtp.bsnl.co.in
8. Send message: [During next conn.](#)
9. User name : [xxx](#)
10. Password : [<your password>](#)
11. Incoming mail server : mail.bsnl.co.in
12. Mailbox type : [POP3](#)
13. Security ports : [Off](#)
14. APOP secure login : [Off](#)
- 15. In user settings**
16. Retrieve : [Headers only](#)
17. Send copy to self : [No](#)
18. Include signature : [No](#)
19. My name : [xxx](#)
- 20. In Automatic retrieval**
21. Header retrieval : [off](#)
22. Now when you start Messaging Application you will see bsnlmail Account there then open it and retrieve your email.
23. You can also send email

Gmail Setup NokiaN97

IMAP4 settings, not the POP3 settings.using a Symbian S60 Smartphone,

1. Enable IMAP in your Gmail settings.
2. Select 'Messaging' > 'Options' > 'Settings' > 'E-mail' > 'Mailboxes.'
3. If you have never set up email on your phone before, select 'Yes' to define a new mailbox. If you already have other mailboxes, select 'Options' and then 'New mailbox.'
4. Select 'Start' to begin the setup wizard.
5. Select 'IMAP4' and then 'Next.'
6. Enter your full email address (including '@gmail.com') as the email address and select 'Next.' Google Apps users, enter your full address in the format 'username@your_domain.com.'
7. Enter 'imap.gmail.com' as the incoming mail server and select 'Next.'
8. Enter 'smtp.gmail.com' as the outgoing mail server and select 'Next.'
9. Select the appropriate access point and then 'Next.'
10. Enter a descriptive name for the email account mailbox name.
11. Once your mailbox is set up, select it from the email mailbox settings screen.
12. Select 'Connection settings' > 'Incoming e-mail.'
13. Enter your address (including '@gmail.com' or '@your_domain.com') and password.
14. Select 'SSL/TLS' for your security (ports) and define your port as '993.'
15. Select 'Back.'
16. Select 'Outgoing e-mail.'
17. Enter your email address (including '@gmail.com' or '@your_domain.com') and password.
18. Select 'StartTLS' for your security (ports) and define your port as '587.'
19. Select 'Back' and change any other settings according to your preferences.
20. Check our recommended client settings, and adjust your client's settings as needed.

Setup Gmail For Mobile

How to configure Gmail Account on N95: (IMP: You must enable POP3 access of Gmail Account. Hint: Look inside Setting and POP forwarding Options on gmail web site)

1. Open Messaging > Options button >Settings > E-mail then
2. Go to Mail box > Options > New mailbox then
- 3. In Mailbox settings**
4. Mailbox : Gmail
5. Access point in use : select bsnlnet or bsnllive
6. My e-mail address : xxx@gmail.com
7. Outgoing mail server : smtp.gmail.com
8. Send message: During next conn.
9. User name : xxx@gmail.com
10. Password : <your password>
11. Incoming mail server : pop.gmail.com
12. Mailbox type : POP3
13. Security ports : On(993/995) or SSL/TLS
14. APOP secure login : Off
- 15. In user settings**
16. Retrieve : Headers only
17. Send copy to self : No
18. Include signature : No
19. My name : xxx
- 20. In Automatic retrieval**
21. Header retrieval : off
22. Now when you start Messaging Application you will see Gmail Account there then open it and retrieve your email.
23. You can also send email, attach images with it etc.

Also there is a faster Gmail application Gmail App for mobile. But with it you can not send attachments or mail photos. This is the best way to configure and use gmail on you handset.

Setup Yahoo mail For Mobile

How to manually setup your Yahoo mail on your mobile phone. Pl. Follow the following steps.

2. Open Messaging > Options button > Settings > E-mail then
3. Go to Mail box > Options > New mailbox then

4. In Mailbox settings

5. Mailbox : [Yahoo mail](#)
6. Access point in use : select [bsnlnet](#) or [bsnllive](#)
7. My e-mail address : [xxx@yahoo.co.in](#)
8. Outgoing mail server : [smtp.mobile.mail.yahoo.com](#)
9. Send message: [During next conn.](#)
10. User name : [xxx](#)
11. Password : [<your password>](#)
12. Incoming mail server : [imap.mail.yahoo.com](#)
13. Mailbox type : [Imap4](#)
14. Security ports : [Off](#)

15. In user settings

16. E-mails to retrieve : [30](#)
17. Retrieve attachments : [No](#)
18. Subscribed folders :
19. Send copy to self : [No](#)
20. Include signature : [No](#)
21. My name : [xxx](#)
22. **In Automatic retrieval**
23. Header retrieval : [off](#)
24. Now when you start Messaging Application you will see Gmail Account there then open it and retrieve your email.
25. You can also send email, attach images with it etc.

Also there is a faster Yahoo mail application Yahoo GO App for mobile. But with it you can not send attachments or mail photos. This is the best way to configure and use Yahoo mail on you handset.

[YahooMail Setup NokiaE72](#)

Steps to setup Yahoo mail on Nokia E72:

1. I am assuming that you have the free Yahoo mail and not the paid version. Since this is the free version you cannot setup the same directly on your mobile. You have to first setup the account at <http://email.nokia.com>

2. When you complete your setup at the site mentioned you will get a message on your mobile.
3. Before the next step, you have to get a GPRS connection on your mobile.
4. Now open the message and follow the instructions, it will ask you for the password if you used to setup the account on <http://email.nokia.com>. Enter that and the setup should complete successfully.
5. Once this first setup is done. Now you can set your GPRS connection to whatever mode you want. You can now also use WLAN based internet connection to update/sync your mail. It's just that first connection to the server that requires GRPS.

Settings for connecting with laptop

HOW to do LAPTOP Configuration

- Install Drivers for Bluetooth in PC/Laptop (if connecting media between PC/Laptop and handset is Bluetooth).
- Drivers for Data cable/IR will be installed when the CD supplied with the handset is installed in PC/Laptop.
- **Install required software in PC/Laptop** (For Example Nokia PC suit for Nokia Handset).
- Required software will be available in the CD supplied along with the handset or can be downloaded from WEB
- Open the application (For eg Nokia PC suit) > Options >
- **"Connect to Internet"** > "Settings" or "network wizard" > "add new connection".
- Select appropriate modem (Bluetooth/data cable/IR) if it is prompted
- Select configuration as **"manual"** and service provider as **"others"**
- Access Point name (APN): **bsnlnet**
- User Name: **blank**
- Password: **blank**
- Dialing Number: ***99#** (if it is prompted)
- Leave all other fields as blank
- It is not required to do any settings in handset to connect to the laptop/PC

Extra Init string

Type the following string

Start > Settings > Control panel > Phone and modems options > Modems > Select modem > Properties > Advanced > Extra init command > Type the following string

AT+CGDCONT=1,"IP","bsnlnet"
